

Get your Position!

A1080-A Full NMEA GPS Module

Developed for indoor use and based on the SiRF Star III low power chip, the A1080-A will benchmark not only sensitivity and power consumption. Being pin-to-pin compatible to Tyco Electronics A1037-A GPS module it will guarantee smallest footprint and easy implementation even in handheld devices and other size optimized battery powered applications. Get your Evaluation Kit and check the outstanding performance of Tyco Electronics' A1080-A!



- Benchmarking sensitivity ■ -159 dBm tracking
- Fastest TTFF (Time To First Fix) ■ < 35 s under cold start condition (typical)
- Very small footprint ■ 19 x 16 mm
- Ultra-low power consumption ■ 31 mA average tracking current
- A-GPS support ■ For fastest start up behavior
- SBAS support ■ For most accurate position calculation

Performance

Channels	20 parallel tracking
Correlators	200,000 plus
Frequency	L1 - 1575 MHz
Sensitivity	
Tracking	-159 dBm
Acquisition (cold start)	-142 dBm
Position accuracy (horizontal)	< 2.5 m CEP autonomous < 2.0 m CEP SBAS
Time to first fix	
Hot start ¹⁾	< 1 s
Warm start ²⁾	< 32 s
Cold ³⁾	< 35 s

Communications

Standard GPS software	
NMEA message switchable	GGA, GSA, GSV, VTG, RMC, GLL
Baudrate (in baud)	4,800 (default) to 34,400
Serial ports	
Tx0	NMEA output
Rx0	NMEA input

Environment

Temperature	
Operating	-30°C to +85°C
Storage	-40°C to +85°C
Humidity	Non-condensing

Power

Input voltage	3.0 to 3.6 VDC
Current draw	
Average acquisition	36 mA (typical)
Tracking	31 mA (typical)
Standby	20 µA (typical)
Antenna supply via VANT	
Voltage range	up to 5.2 V
Max. allowed current ⁴⁾	50 mA

Mechanicals

Dimensions	16.2 mm x 19 mm x 2.4 mm 0.75" x 0.64" x 0.095"
Weight	1 g, < 0.05 oz

1) The receiver has estimates of time/date/position and valid almanac and ephemeris data.
 2) The receiver has estimates of time/date/position and almanac.
 3) The receiver has no estimate of time/date/position, and no recent almanac.
 4) An external current limiter is suggested to avoid damage in fault conditions.

Positioning Receiver Portfolio

With the mission to support our customers to implement GPS functionality into their systems, Tyco Electronics is offering a large product portfolio to cover almost all integration possibilities in an easy way. A dedicated R&D team located in Ottobrunn, Germany develops sensitive positioning solutions based on state of the art technologies. All GPS products are manufactured in our ISO9001 and TS16949 certified factory inside the EU. Beyond that our modules follow RoHS standard and are 100% electrically and functionally tested prior packaging. This way we constantly guarantee high quality products.

Products shown in actual size



A1037-A




A1029-A/-C



A1080-A



A1030-A



A1035-C/-D

	1 PPS	Antenna active	Antenna passive	Antenna patch onboard	Antenna status detection	Assisted GPS	Connection plug-in	Connection solderable	Data logging	Dead reckoning	Differential GPS RTCM input	Flash, programmable	GPIO	GPS/UTC raw data	I2C interface	Memory free flash (byte)	free SRAM (byte)	Processor: available power	ROM	SBAS support	SPI interface	TCXO	UART NMEA	USB interface	UTM projection
A1037-A	●	●				●		●											●	●		●	●		
A1029-A	●	●	●		●	●		●		●	●	●	●	●	●	80k/16k	3 MIPS		●	●		●	●		●
A1029-B	●	●	●		●	●	●			●	●	●	●	●	●	80k/16k	3 MIPS		●	●		●	●		●
A1029-C	●	●	●		●	●		●		●	●	●	●	●	●	80k/16k	3 MIPS		●	●		●	●		●
A1029-D	●	●	●		●	●	●			●	●	●	●	●	●	80k/16k	3 MIPS		●	●		●	●		●
A1080-A	●	●				●		●						●					●	●		●	●		
A1030-A	●	●	●		●	●	●		●	●	●	●	●	●	●	4M/2M	3 MIPS		●	●		●	●	●	●
A1035-C		●		●		●	●					●		●		80k/16k	3 MIPS		●	●		●	●		●
A1035-D	●	●		●		●	●							●					●	●		●	●		

● Standard firmware: revision 1xx
 ● Standard firmware: revision 2xx
 ● With custom firmware support

The information provided herein is believed to be reliable at press time. Tyco Electronics Power Systems assumes no responsibility for inaccuracies or omissions. Tyco Electronics Power Systems assumes no responsibility for the use of this information, and all such information shall be entirely at the users own risk. Prices and specifications are subject to change without notice. Tyco Electronics Power Systems does not authorize or warrant any of its products for use in life-support devices and / or systems.

Headquarters EMEA:
Tyco Electronics
Power Systems
 Finsinger Feld 1
 85521 Ottobrunn, Germany

Tel.: +49 (0)89 6089-838
 Fax: +49 (0)89 6089-835

gps@tycoelectronics.com
 www.tycoelectronics.com/gps

Your Partner:

 **Tyco Electronics**
 Our commitment. Your advantage.